

Emergency Exit Device with LED Back Lighting

The Smart Em operates the same way as the standard Em Rex[®] (Emergency Exit Device) but it operates on either 12Vdc or 24Vdc.


The Smart EM[®] also has LED Back Lighting which allows both easy location and greater safety in emergencies involving areas of limited lighting.

Features:

- ▼ No breaking of glass when operated
- ▼ Two outputs: one set to break lock power and one set for status monitoring
- ▼ Visual confirmation of activation
- ▼ Audible confirmation of activation
- ▼ Ancillary input for remote operation of sounder
- ▼ Minimal moving parts
- ▼ LED back lighting to allow the unit to be easily located
- ▼ Field resettable unit. A reset tool is supplied with every unit
- ▼ Compatible with the Em Cover for extra protection
- ▼ Fits the TDL Surface Mounting Kit and optional surrounds
- ▼ Em Cover can be fitted to this unit to avoid malicious use
- ▼ The face plate will not deteriorate over time and is easily cleaned



Specifications:

- ▼ Single gang profile fits standard electrical flush box
- ▼ Power requirements 10 to 24Vdc (only if using on-board sounder)
- ▼ 10mA at 13.6 Vdc and 5mA at 27.6 Vdc
- ▼ Two sets of Clean N/O, N/C outputs
- ▼ The contacts are rated at 2 Amp @ 30Vdc
- ▼ LED back lighting
- ▼  C-Tick Certified & complies with BS 5839 Pt 2. Standard for "Break-Glass Panels"

Product Code:

- ▼ Smart Em Rex